

SUBSTITUTE CLAIMS

Serial No. 09/251,297

February 27, 2006

1. (Previously Presented) A range measuring device comprising an ultra-wideband (UWB) transmitter and receiver, said device comprising:

a switched impulse generator to generate a low-level waveform adaptive ultra-wideband signal comprised of a low-level UWB energy pulse,

a wave filter that filters said low-level UWB energy pulse to define a center frequency thereof and to produce a filtered low-level UWB energy pulse having a given bandwidth and center-frequency;

an antenna responsive to said wave filter to radiate a transmitted signal representing said filtered low-level UWB energy pulse; and

a receiver that receives a representation of the transmitted signal reflected from an object after the antenna completes radiating the transmitted signal.

2. (Currently Amended) A communication system utilizing an ultra-wideband (UWB) transmitter, said system comprising:

a switched impulse generator to generate a low-level ultra-wideband signal characterized by a series of UWB pulses, said switched impulse generator including one of an on-off switched oscillator, an oscillator having a time-gated dc bias that alternately biases the oscillator on and off, and an impulse-gated mixer that mixes an oscillator output;

Serial No. 09/251,297
February 27, 2006

a filter responsive to said switched impulse generator to filter said UWB pulses thereby to produce filtered UWB pulses;

an antenna responsive to said filter to radiate a representation of said filtered UWB pulses; and

a receiver that detects individual ones of radiated representations of said UWB pulses, said receiver including a variable attenuator coupled to a receiving antenna to adjust attenuation levels thereof based on a rate of error detection of said radiated ultra-wideband ~~pulse~~ pulses received at said receiver; and a detector to detect an output of said variable attenuator.

3. (Previously Presented) A method of detecting an object utilizing ultra-wideband transmitting techniques, said method comprising:

impulse-switching an oscillator to generate a low-level ultra-wideband signal;

wave filtering said low-level ultra-wideband signal;

after said wave filtering step, transmitting a signal representing said low-level ultra-wideband signal; and

after said transmitting step, receiving from said object a reflected pulse of said ultra-wideband signal thereby to detect said object, said receiving step including variably attenuating the reflected pulse to adjust an attenuation level thereof according detected error in the reflected pulse received at said receiver; and detecting a signal produced by the reflected pulse after said variably attenuating.

Serial No. 09/251,297
February 27, 2006

4. (Previously Presented) A waveform adaptive ultra-wideband transmitter comprising:

a signal generator to generate a series of discrete low-level ultra-wideband signals comprised of short bursts of RF energy having a carrier frequency defined cycle periodicity in respective ones of said short bursts;

a waveform adapter responsive to said low-level ultra-wideband signals and including at least one of a bandpass filter, a mixer, a pulse shaper, and an attenuator that controls one of frequency, pulse shape, bandwidth, phase, multi-level amplitude, and multi-level attenuation of said low-level ultra-wideband signals, said waveform adapter controlling said low-level ultra-wideband signals on a dynamic, real-time basis; and

an antenna responsive to said waveform adapter to radiate ultra-wideband signals.

5. (Canceled)

6. (Previously Presented) The range measuring device as recited in claim 1, wherein said receiver comprises at least one tunnel diode responsive to an echo pulse.

7. (Previously Presented) The range measuring device as recited in claim 1, further comprising an amplifier that amplifies said filtered low-level ultra-wideband energy pulse.

8. (Previously Presented) The range measuring device of claim 7, wherein said wave filter comprises one of a band-pass filter and a pulse shaper.

Serial No. 09/251,297
February 27, 2006

9. (Previously Presented) The range measuring device of claim 1 wherein said wave filter defines a bandwidth of the signal radiated by the antenna to reduce out-of-band emissions radiated by said antenna.

10. (Previously Presented) The range measuring device of claim 1, wherein the receiver includes:

a variable attenuator coupled to a receiving antenna to adjust attenuation levels thereof based on a rate of error detection of the radiated ultra-wideband signal received at said receiver; and

a detector to detect an output of said variable attenuator.

11. (Previously Presented) The range measuring device of claim 10, wherein said detector comprises a tunnel diode and said variable attenuator adjusts said attenuation by alternately applying noise and received information signals to said tunnel diode.

12. (Previously Presented) The range measuring device of claim 11, further including a controller that digitally controls the variable attenuator according to signals received during respective noise dwells and data dwells to enable the detector to discriminate between noise and range measuring signals.

13. (Previously Presented) The range measuring device of claim 12, wherein said controller utilizes a bit error rate to discriminate between noise and range measuring signals.

Serial No. 09/251,297
February 27, 2006

14. (canceled)

15. (Previously Presented) The communication system as recited in claim 2, further comprising an amplifier interposed between said filter and antenna to amplify the filtered UWB pulses.

16. (Previously Presented) The communication system as recited in claim 15, wherein said filter comprises one of a band-pass filter and a pulse shaper that substantially confines radiated emissions of said antenna within a given passband.

17. (Canceled)

18. (Previously Presented) The communication system as recited in claim 2, wherein said detector comprises a tunnel diode and said variable attenuator adjusts said attenuation by alternately applying noise and received information signals to said tunnel diode.

19. (Previously Presented) The communication system as recited in claim 18, further including a controller that digitally controls the variable attenuator according to signals received during respective noise dwells and data dwells to enable the detector to discriminate between said noise and received information signals.

20. (Previously Presented) The communication system as recited in claim 19, wherein said controller utilizes a

Serial No. 09/251,297
February 27, 2006

bit error rate to discriminate between noise and information signals.

21. (Previously Presented) The method of claim 3, further comprising the step of providing a tunnel diode to receive the reflected pulse.

22. (Currently Amended) The method of claim 3, further comprising, after ~~generating~~ impulse-switching to generate said low-level ultra-wideband signal, amplifying said low-level ultra-wideband signal.

23. (Previously Presented) The method of claim 22, wherein said filtering comprises one of bandpass filtering and pulse shaping of said low-level ultra-wideband signal in order to substantially confine said signal representing said low-level ultra-wideband signal within a given passband.

24. (Previously Presented) The method of claim 23, further comprising the step of defining a bandwidth of the signal radiated from the object.

25. (canceled)

26. (Previously Presented) The method of claim 3, further including providing a tunnel diode to detect the reflected pulse and adjusting said variably attenuating by alternately applying noise and received information signals to said tunnel diode.

Serial No. 09/251,297
February 27, 2006

27. (Previously Presented) The method of claim 26, further including digitally controlling said variably attenuating of the reflected pulse according to signal received during respective noise dwells and data dwells to enable discrimination between noise and signals representing the reflected pulse.

28. (Previously Presented) The method of claim 27, including utilizing bit error rate to discriminate between noise and signals representing the reflected pulse.

29. (Currently Amended) In a one-pulse, one-bit ultra-wideband (UWB) transceiver system, a method of detecting transmitted information comprising:

generating a series of low-level UWB pulses of short duration,

modulating respective ones of said low-level UWB pulses according to respective bits of information,

bandpass filtering the modulated low-level UWB pulses to produce filtered low-level UWB pulses and to reject out-of-band emissions,

radiating a filtered representation of said modulated low-level UWB pulses, and

detecting at a receiver respective bits of information associated with respective ones of said UWB pulses.

30. (Previously Presented) The method of claim 29, wherein said generating step includes generating a short burst of RF energy having a carrier frequency associated with said UWB pulses.

Serial No. 09/251,297
February 27, 2006

31. (Previously Presented) The method of claim 30, wherein said short burst comprises a few cycles of RF energy that define a center frequency.

32. (Previously Presented) The method of claim 31, wherein said bandpass filtering includes wave filtering said low-level UWB pulses.

33. (Previously Presented) The method of claim 31, wherein said UWB pulses have pulse-to-pulse coherency.

34. (Previously Presented) The method of claim 31, wherein said UWB pulses lack pulse-to-pulse coherency.

35. (Previously Presented) The method of claim 31, wherein said generating step comprises impulse-driving an oscillator to produce said UWB pulses.

36. (Previously Presented) The method of claim 31, wherein said generating step comprises impulse-driving a mixer which, in turn, gates an output of an oscillator to produce said UWB pulses.

37. (Previously Presented) The method of claim 36, further comprising the step of impulse-driving the mixer with a low voltage having a short rise time thereby to enable switching at hundreds of megabits per second.

38. (Previously Presented) The method of claim 31, wherein said generating step comprises time-gating a dc bias of an oscillator to produce said UWB pulses.

Serial No. 09/251,297
February 27, 2006

39. (Previously Presented) The method of claim 31, wherein said modulating step comprises amplitude modulating said UWB pulses by on-off switching of the generating step.

40. (Previously Presented) The method of claim 31, wherein said modulating step comprises multi-level amplitude modulating said UWB pulses produced by the generating step.

41. (Previously Presented) The method of claim 31, wherein said modulating step comprises phase-shifting said UWB pulses.

42. (Previously Presented) The method of claim 35, wherein said oscillator comprises a voltage-controlled oscillator and said modulating step comprises frequency-shifting the voltage-controlled oscillator according to an information signal.

43. (Previously Presented) The method of claim 42, further comprising the step of frequency-hopping the oscillator.

44. (Previously Presented) The method of claim 31, wherein said detecting step includes utilizing a tunnel diode to detect respective bits of information.

45. (Previously Presented) The method of claim 44, further comprising utilizing a bit error rate to distinguish between error and information signals.

Serial No. 09/251,297
February 27, 2006

46. (Previously Presented) The method of claim 31 further comprising, prior to said radiating step, amplifying the filtered low-level UWB pulses.

47. (Previously Presented) The method of claim 46, further comprising gating said amplifying in accordance with occurrence of said low-level UWB pulses in said generating step.

48. (Previously Presented) The method of claim 31, wherein said short duration ranges between a sub-nanoseconds to a few nanoseconds.

49. (canceled)

50. (Currently Amended) A method of communicating data by transmitting and detecting an ultra wideband pulse (UWB), said method comprising:

generating a low-level UWB pulse that includes an energy burst having a few cycles of RF energy of a defined carrier frequency,

filtering the energy burst to reject out-of-band emissions,

radiating a filtered representation of said energy burst, and

after said radiating step, detecting a bit of information associated with said filtered representation of said energy burst, whereby to communicate data.

51. (Previously Presented) The method of claim 50, wherein said filtering step includes wave filtering said energy burst to reject out-of-band emissions.

Serial No. 09/251,297
February 27, 2006

52. (Previously Presented) The method of claim 50, wherein said generating step includes on-off switching of an oscillator to produce said energy burst.

53. (Previously Presented) The method of claim 50, wherein said generating step includes impulse-driving a mixer which, in turn, gates an output of an oscillator to produce said UWB pulse.

54. (Previously Presented) The method of claim 50, wherein said generating step includes time-gating a dc bias of an oscillator to produce said energy burst.

55. (Previously Presented) The method of claim 50, wherein said generating step includes impulse-driving a filter to produce said energy burst.

56. (canceled)

57. (canceled)